

## 4" Square Boxes, Drawn

## 4" Square Boxes, Deep, Drawn

## 4" Square Covers



### Features

- Drawn
- 1- $\frac{1}{2}$ " & 2- $\frac{1}{4}$ " deep
- Available in multiple KO sizes, with or without concentric KOs

### Applications

- 4" square drawn junction boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices. Square boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions

### Standard Material

- Galvanized steel

Catalog Number	Description	Knockouts		Cubic Inches	Ship Case	Weight/Case
		Sides	Bottom			
<b>BOXES</b>						
52151- $\frac{1}{2}$	1- $\frac{1}{2}$ " deep $\frac{1}{2}$ " KO	(12)- $\frac{1}{2}$ "	(2)- $\frac{1}{2}$ " (2)- $\frac{3}{4}$ "	21	50	31
52151- $\frac{3}{4}$	1- $\frac{3}{4}$ " deep $\frac{3}{4}$ " KO	(8)- $\frac{3}{4}$ "	(2)- $\frac{1}{2}$ " & (2)- $\frac{3}{4}$ "	21	50	31
52151- $\frac{1}{2}$ & $\frac{3}{4}$	1- $\frac{1}{2}$ " deep $\frac{1}{2}$ " & $\frac{3}{4}$ " KO	(8)- $\frac{1}{2}$ " & (4)- $\frac{3}{4}$ "	(2)- $\frac{1}{2}$ " & (2)- $\frac{3}{4}$ "	21	50	31
52171- $\frac{1}{2}$	2-1/8" deep $\frac{1}{2}$ " KO	(12)- $\frac{1}{2}$ "	(2)- $\frac{1}{2}$ " (2)- $\frac{3}{4}$ "	30.5	50	41
52171- $\frac{3}{4}$	2-1/8" deep $\frac{3}{4}$ " KO	(8)- $\frac{3}{4}$ "	(2)- $\frac{1}{2}$ " (2)- $\frac{3}{4}$ "	30.5	50	39
52171- $\frac{1}{2}$ & $\frac{3}{4}$	2-1/8" deep $\frac{1}{2}$ " & $\frac{3}{4}$ " KO	(8)- $\frac{1}{2}$ " & (4)- $\frac{3}{4}$ "	(2)- $\frac{1}{2}$ " (2)- $\frac{3}{4}$ "	30.5	50	41
52171-1	2-1/8" deep 1" KO	(8)-1"	(2) $\frac{1}{2}$ " & (2) $\frac{3}{4}$ "	30.5	50	41
<b>COVERS</b>						
52C1	Blank Flat (1) Hole & (1) Slot	-	-	-	50	31
52C6	Flat (1) $\frac{1}{2}$ KO, (1) Hole & (1) Slot	-	(1)- $\frac{1}{2}$ "	-	50	31



52C1



52C6